

### 3.0x2.0mm SURFACE MOUNT LED LAMP

Blue

Part Number: AA3021VBS/D



**ATTENTION** OBSERVE PRECAUTIONS FOR HANDLING **ELECTROSTATIC** DISCHARGE SENSITIVE **DEVICES** 


### **Features**

- 3.0mm x 2.0mm, 1.3mm high, only minimum space required.
- Suitable for compact optoelectronic applications.
- Low power consumption.
- Package: 2000pcs / reel.
- Moisture sensitivity level : level 3.
- RoHS compliant.

### **Descriptions**

- The Blue source color devices are made with InGaN Light Emitting Diode.
- Electrostatic discharge and power surge could damage the LEDs.
- It is recommended to use a wrist band or antielectrostatic glove when handling the LEDs.
- All devices, equipments and machineries must be electrically grounded.

## **Package Dimensions**



- 1. All dimensions are in millimeters (inches).
- 2. Tolerance is  $\pm 0.2 (0.008")$  unless otherwise noted.
- 3. The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.

  4. The device has a single mounting surface. The device must be mounted according to the specifications.


SPEC NO: DSAN2843 **REV NO: V.2B** DATE: SEP/09/2014 PAGE: 1 OF 6 APPROVED: WYNEC CHECKED: Allen Liu DRAWN: L.Q.Xie ERP: 1201006410

### **Handling Precautions**

Compare to epoxy encapsulant that is hard and brittle, silicone is softer and flexible. Although its characteristic significantly reduces thermal stress, it is more susceptible to damage by external mechanical force.


As a result, special handling precautions need to be observed during assembly using silicone encapsulated LED products. Failure to comply might lead to damage and premature failure of the LED.

1. Handle the component along the side surfaces by using forceps or appropriate tools.



2. Do not directly touch or handle the silicone lens surface. It may damage the internal circuitry.






3. Do not stack together assembled PCBs containing exposed LEDs. Impact may scratch the silicone lens or damage the internal circuitry.



- 4.1. The inner diameter of the SMD pickup nozzle should not exceed the size of the LED to prevent air leaks.
- 4.2. A pliable material is suggested for the nozzle tip to avoid scratching or damaging the LED surface during pickup.
- 4.3. The dimensions of the component must be accurately programmed in the pick-and-place machine to insure precise pickup and avoid damage during production.



5. As silicone encapsulation is permeable to gases, some corrosive substances such as  $H_2S$  might corrode silver plating of leadframe. Special care should be taken if an LED with silicone encapsulation is to be used near such substances.

SPEC NO: DSAN2843 REV NO: V.2B DATE: SEP/09/2014 PAGE: 2 OF 6
APPROVED: WYNEC CHECKED: Allen Liu DRAWN: L.Q.Xie ERP: 1201006410

### **Selection Guide**

Part No.	Dice	Lens Type	lv (mcd) [2] @ 20mA		Viewing Angle [1]
		2.	Min.	Тур.	201/2
AA3021VBS/D	Blue (InGaN)	Water Clear	200	450	125°

### Notes:

- θ1/2 is the angle from optical centerline where the luminous intensity is 1/2 of the optical peak value.
   Luminous intensity/ luminous Flux: +/-15%.
   Luminous intensity value is traceable to the CIE127-2007 compliant national standards.

# Electrical / Optical Characteristics at TA=25°C

Symbol	Parameter	Device	Тур.	Max.	Units	Test Conditions
λpeak	Peak Wavelength	Blue	465		nm	IF=20mA
λD [1]	Dominant Wavelength	Blue	470		nm	IF=20mA
Δλ1/2	Spectral Line Half-width	Blue	22		nm	IF=20mA
С	Capacitance	Blue	100		pF	VF=0V;f=1MHz
VF [2]	Forward Voltage	Blue	3.3	4	V	IF=20mA
lr	Reverse Current	Blue		50	uA	V <sub>R</sub> =5V


- 1.Wavelength: +/-1nm.
- 2.Forward Voltage: +/-0.1V.
- 3. Wavelength value is traceable to the CIE127-2007 compliant national standards.
- 4.Excess driving current and/or operating temperature higher than recommended conditions may result in severe light degradation or premature failure.

### Absolute Maximum Ratings at TA=25°C

And of the control of					
Parameter	Blue				
Power dissipation	120	mW			
DC Forward Current	30	mA			
Peak Forward Current [1]	100	mA			
Reverse Voltage	5	V			
Operating Temperature	-40°C To +85°C				
Storage Temperature	-40°C To +85°C				
Storage remperature	-40 C 10 +85°C				

1. 1/10 Duty Cycle, 0.1ms Pulse Width.

SPEC NO: DSAN2843 **REV NO: V.2B** DATE: SEP/09/2014 PAGE: 3 OF 6 APPROVED: WYNEC **CHECKED: Allen Liu** DRAWN: L.Q.Xie ERP: 1201006410




SPEC NO: DSAN2843 REV NO: V.2B DATE: SEP/09/2014 PAGE: 4 OF 6
APPROVED: WYNEC CHECKED: Allen Liu DRAWN: L.Q.Xie ERP: 1201006410

### AA3021VBS/D

Reflow soldering is recommended and the soldering profile is shown below. Other soldering methods are not recommended as they might cause damage to the product.

Reflow Soldering Profile For Lead-free SMT Process.




- NOTES:

  1.We recommend the reflow temperature 245°C(+/-5°C). The maximum soldering temperature should be limited to 260°C.


  2.Don't cause stress to the epoxy resin while it is exposed to high temperature.

  3.Number of reflow process shall be 2 times or less.


## **Recommended Soldering Pattern** (Units: mm; Tolerance: ± 0.1)



# **Reel Dimension**



**Tape Dimensions** (Units: mm)




SPEC NO: DSAN2843 **APPROVED: WYNEC** 

**REV NO: V.2B CHECKED: Allen Liu** 

DATE: SEP/09/2014 DRAWN: L.Q.Xie

PAGE: 5 OF 6 ERP: 1201006410

# PACKING & LABEL SPECIFICATIONS USER DIRECTION OF FEED LABEL 2,000pcs / Reel 1 Reel / Bag OUTSIDE LABEL OUTSIDE



LABEL

Kingbright

30K / 55# Box

### Terms and conditions for the usage of this document

Kingbright

60K / 56# BOX

- 1. The information included in this document reflects representative usage scenarios and is intended for technical reference only.
- 2.The part number, type, and specifications mentioned in this document are subject to future change and improvement without notice. Before production usage customer should refer to the latest datasheet for the updated specifications.
- 3. When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, Kingbright will not be responsible for any subsequent issues.
- 4.The information in this document applies to typical usage in consumer electronics applications. If customer's application has special reliability requirements or have life-threatening liabilities, such as automotive or medical usage, please consult with Kingbright representative for further assistance.
- 5. The contents and information of this document may not be reproduced or re-transmitted without permission by Kingbright.
- 6.All design applications should refer to Kingbright application notes available at <a href="http://www.KingbrightUSA.com/ApplicationNotes">http://www.KingbrightUSA.com/ApplicationNotes</a>

 SPEC NO: DSAN2843
 REV NO: V.2B
 DATE: SEP/09/2014
 PAGE: 6 OF 6

 APPROVED: WYNEC
 CHECKED: Allen Liu
 DRAWN: L.Q.Xie
 ERP: 1201006410